




## DATA SHEET

# BJT-4000V2 RHINO



## MOBILE JUMP STARTER 12/24 Volt



Durst Industries (Aust.) Pty Ltd.  
1/11 Packard Ave. Castle Hill  
NSW 2154 Australia

 [DURST.COM.AU](http://DURST.COM.AU)  
 [SALES@DURST.COM.AU](mailto:SALES@DURST.COM.AU)  
 INTL +61 2 9660 1755



### **Model**

- › BJT-4000V2

### **Description**

- › 12 Volt and 24 Volt Portable Jump Starter

### **Performance At 12 Volts**

- › Cold Cranking Amps: CCA 900
- › Peak Amps: PA 7,600

### **At 24 Volts**

- › Cold Cranking Amps: CCA 450
- › Peak Amps: PA 3,800

### **Battery**

- › 2 x 22 Ah Durst 212 HP AGM, Local stock, user serviceable

### **Charger**

- › Automatic Smart Charger BCS-A 1206 12 Volts 6 Amps

### **Features**

- › Designed in Australia for Australian Conditions and Climate
- › Complies with WHS Regulations
- › Powder Coated Steel Cabinet
- › Reverse Polarity Protection Buzzer - LED Warning Light
- › Anti Spike Protection, Local stock, user serviceable
- › Battery Isolation Switch - 12Volt - Off - 24 Volt  
Local stock, user serviceable
- › Voltage Selection and Indicator Light
- › Will Jump start vehicles - with dead flat Batteries
- › Digital Voltmeter to monitor Voltage status with colours
- › Long Life - and maintenance free
- › Fuse: Ignition Protected Auto Reset - in case of short circuit  
Maintenance Free, no replacement required.
- › Auto-activated Fuse installation
- › Aircraft Models for various Voltages
- › Custom Modifications available on request



### ***Physical and Dimensional Properties***

- › Each unit weighs approximately 25 Kg
- › Width 280 mm
- › Length 260 mm
- › Height 360 mm
- › Cable Length 1.5 m
- › Cable Size 50 mm<sup>2</sup> (AWG2/0) Superflex, dual insulated pure multi-strand copper
- › Anderson to Clamp (Standard),  
Anderson to Anderson and Anderson to CAT (Optional extras)
- › Clamps: 1000A Insulated Extra heavy duty, nickel plated copper

### ***Functions***

- › Multifunction Digital Volt Meter
- › Warning Buzzer
- › Computer Safe
- › Optional trolley available
- › DC Charger: Optional
- › AC Charger: Automatic, Durst BCS-A1206

### ***Serviceability***

- › User serviceable, does not void warranty

### ***Uses***

- › Portable high-capacity mobile jump starter.
- › Suitable for Car/Light Commercial vehicle dealer workshops, Panel Beaters, Minibus repairers, Mining Companies, Aviation, Defence, Councils, TAFE, Hire Companies, Auction Yards.

### ***Documentation***

- › Bar Code Number: 934608000341
- › Product Specification Manual - PS 02
- › Work Instruction Manual-WI 02
- › Product Costing Manual-PC 02