



PS MANUAL

GANG CHARGERS

1.0 Model **BC- 308-72**

2.0 Description

Dual Channel Industrial Gang Charger



Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue
Castle Hill NSW 2154 Australia





3.0 Features

- 37% Capacity of **BC-1696** Model
- Variable Course and Fine Current Adjustment.
- Variable Voltage
- Fuse Protected
- Circuit Indicator Lights
- Designed for Continuous use, fan cooled
- Heavy Duty Powder coated Steel Case
- Heavy Duty Rectifiers
- Copper Wound Transformers
- Separately Switched Copper Wound Transformers
- Large easy to read Meters
- Complies with Australian Electrical Standards
- Australian Designed and Manufactured

4.0 Physical and Dimensional Properties

- Each unit weighs approximately 20.0 Kg
- Width 360 mm
- Length 220 mm
- Height 310 mm
- 1 x **LS-213** = 2 off 6mm Cable 50Amp Clamps 2.5m Long
&
5 off 4mm Cable 25Amp Clamps 500mm Long

5.0 Performance

- AC Input 240 Volt
- Frequency 50 Hz
- DC Output 8 Amps
- Charge Voltage 12 - 72 Volt

6.0 Uses

- Designed to suit the Battery Manufactures, suppliers and the Battery service Industry
- Suitable for Automotive, Marine, Aircraft & Stationary engines
Featuring 11 Variations for charging to a maximum 72 Volts 8 Amps

7.0 Documentation

- Bar Code Number: **9346080000679**
- Product Specification Manual -PS 41
- Work Instruction Manual - WI 41
- Product Costing Manual - PC 41

