



PS MANUAL

## BCS-BATTERY CHARGERS

1.0 Model **BCS-A1206**

2.0 Description

12 Volt 6 Amp SmartCharger Battery Charger



Durst Industries Australia Pty. Ltd.

[durst.com.au](http://durst.com.au)

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue  
Castle Hill NSW 2154 Australia



**3.0**     **Features**

- Fully Automatic, Fast and Safe.
- Overcharging Protection.
- Short Circuit Protection
- High Efficiency
- Three stage Charging indicator LED's
- Eliminates Sulphation
- Compact and Lightweight
- Leads and Battery Clamps
- Australian Electrical Standard & EMC Compliant
- Available with Optional plug to suit Mobility Scooters, wheel chairs etc

**4.0**     **Physical and Dimensional Properties**

- Each unit weighs approximately 0.5 Kg
- Width 70 mm
- Length 155 mm
- Height 48 mm
- Carton Dimensions: 240 x 190 x 55
- Colour: Red

**5.0**     **Performance**

- Voltage 100-240 Volt
- Frequency 47-63 Hz
- Output Current: 6 Amps
- Boost Voltage 14.4 Volts
- Float Voltage 13.7 Volts
- Wattage: 88W
- Battery size Ahr 18 Ahr - 60 Ahr

**6.0**     **Uses**

- SmartCharger Battery Charger.
- Suitable for Automotive, Marine, Mobile Home or Caravan, Mobility Appliances, Golf Carts, Solar, Deep Cycle, UPS Standby.

**7.0**     **Documentation**

- Bar Code Number: **9346080001416**
- Product Specification Manual – PS 154
- Work Instruction Manual     - WI 154
- Product Costing Manual        - PC 154

