



PS MANUAL

BCS-BATTERY CHARGERS

1.0 Model **BCS-A1220**

2.0 Description

12 Volt 20Amp SmartCharger Battery Charger



Durst Industries Australia Pty. Ltd.

durst.com.au

Phone: +61 2 9660 1755

Unit 1, 11 Packard Avenue
Castle Hill NSW 2154 Australia





3.0 Features

- Fully Automatic, Fast and Safe.
- Overcharging Protection.
- Short Circuit Protection
- High Efficiency
- Three stage Charging indicator LED's
- Eliminates Sulphation
- Compact and Lightweight
- Leads and Battery Clamps
- Australian Electrical Standard & EMC Compliant
- Available with Optional plug to suit Mobility Scooters, wheel chairs etc

4.0 Physical and Dimensional Properties

- Each unit weighs approximately 1.2 Kg
- Width 118 mm
- Length 190 mm
- Height 58 mm
- Carton Dimensions: 280 x 230 x 100
- Colour: Red

5.0 Performance

- Voltage 200-240 Volt
- Frequency 47-63 Hz
- Output Current: 20 Amps
- Boost Voltage 14.4 Volts
- Float Voltage 13.7 Volts
- Wattage: 294W
- Battery size Ahr 60 Ahr - 300 Ahr

6.0 Uses

- SmartCharger Battery Charger.
- Suitable for Automotive, Marine, Mobile Home or Caravan, Mobility Appliances, Golf Carts, Solar, Deep Cycle, UPS Standby.

7.0 Documentation

- Bar Code Number: **9346080001447**
- Product Specification Manual – PS 157
- Work Instruction Manual - WI 157
- Product Costing Manual - PC 157

