

BJT-200 V2 DATA SHEET



High-Performance Mobile Jump Starter 12Volt and 24 Volt





Durst Industries (Aust.) Pty Ltd. 1/11 Packard Ave. Castle Hill NSW 2154 Australia





FEATURES

- > 12V/24V Switchable Operation: Easily switch between 12V and 24V modes for versatile use.
- **> Reverse Polarity Warning Buzzer:** Audible alert for incorrect connections, ensuring safety.
- **> Anti Spike Protection:** Protects sensitive vehicle electronics from voltage spikes.
- **> Auto Reset Fuse:** Automatically resets in case of a short circuit, reducing downtime.
- **> Extended Life Operation:** Designed for long-lasting, maintenance-free performance.
- **> Powder Coated Steel Enclosure:** Durable and weather-resistant finish for harsh conditions.
- **> Quality Durable Build:** All components are serviceable for extended product life.
- > Wheeled Trolley: Easy to transport across workshops or job sites.
- > High Performance Operation:
 - > 12V: 1600 Cold Cranking Amps (CCA)
 - > 24V: 800 Cold Cranking Amps (CCA)
- > Extended Cranking Time: Reliable and powerful performance for hard-to-start engines.
- New V2 Model: Improved safety features and enhanced build quality.

PHYSICAL AND DIMENSIONAL PROPERTIES

> Weight: Approximately 57 kg

> Dimensions:

> Width: 570 mm
> Length: 330 mm
> Height: 620 mm
> Cable Length: 2.0 m

> Cable Size: Primary 70mm² (LS-704-AP350RD)



PERFORMANCE:

- > At 12 Volts:
 - > Cranking Amps (CA): 1960
 - > Cold Cranking Amps (CCA): 1600
 - **> Peak Amps (est.):** 7000
- > At 24 Volts:
 - > Cranking Amps (CA): 980
 - > Cold Cranking Amps (CCA): 800
 - **> Peak Amps (est.):** 3500
- > Charger: Automatic SmartCharger BCS-A1210, 24 Volts, 12 Amps

APPLICATIONS:

> Ideal for use in car and truck dealerships, panel beaters, bus repair workshops, mining companies, aviation and defence sectors, councils, TAFEs, hire companies, and auction yards.

DOCUMENTATION:

> Bar Code Number: 934608000358